

# Features and Benefits

**ANTRONIX®**

## ARA1-15EQ/AC Advanced Equalized Residential Amplifier

The Antronix Equalized Advanced Residential Amplifier (ARA-EQ) was designed with the latest technology for reliable subscriber premise amplification. The ARA1-15-EQ generates forward gain while providing 7 dB of cable equalization for cable drops in excess of 150 feet. By using Gallium Arsenide technology, the ARA provides improved distortion and noise performance required for today's bi-directional digital applications. This is the first equalized residential amplifier to utilize the Antronix patented CamPort®. This auto-seizing F-port ensures maximum contact area and reliability for multimedia applications. Ideal for both indoor and outdoor applications, the ARA was engineered to withstand the harshest environmental threats with the capability to endure repeated high power surges. The lightweight powder coated AL360 housing provides superior corrosion resistance for quality performance year after year.



- **7 dB Cable Equalization (52-1002 MHz)**  
Provides cable equalization to compensate for long cable drops.
- **CamPort® Auto-Seizing F-Port**  
Patented auto-seizing F-port features a "Cam Activated Mechanism" to provide full contact pressure (> 2000 grams) on the center conductor for maximum reliability.
- **3 dB Noise Figure**  
Provides clean amplification of weak signals to overcome the poor noise figure in TV tuners and converters.
- **6 kV Combination Wave Surge Protection**  
Unique surge protection on all RF ports without the use of arc gaps which may cause high impulse noise during discharge.
- **Gallium Arsenide Technology for Low Distortion**  
Provides improved distortion and noise performance.
- **15 psi Sealed SCTE Compliant CamPort®**  
Sealed brass CamPort prevents water migration.
- **5-42/52-1002 MHz Diplex Filter**  
True 5-42 MHz return band and full 1 GHz downstream spectrum for more useable bandwidth.
- **Weather Sealed Housing with RFI Gasket**  
Guarantees repeatable 120 dB RFI shielding.
- **Powder Coated AL 360 Aluminum Housing**  
Provides the most corrosion resistant protection against salt, fog and rust.
- **Powered Locally or Remotely**  
Power the amplifier locally with supplied adaptor or remotely with an optional power inserter.
- **PTC Short-Circuit Protected UL Listed Adaptor**  
Self-resetting circuit protection provides safe protection against short-circuits to minimize maintenance costs.
- **Dual Compartment Power Inserter**  
Provides high AC to RF isolation to minimize ingress.
- **Exceeds all SCTE Standards**
- **5 Year Warranty**

## Electrical Specifications ARA1-15EQ/AC

Return Specifications	Freq (MHz)	Max	Min
<b>Gain</b> (dB nominal)	52	—	7 ± 0.5
	1002	—	14 ± 0.5
<b>Return Loss</b> (dB)	52-1002	—	20
<b>Noise Figure</b> (dB)	52-1002	3.0	—
<b>Flatness</b> (dB)	52-1002	± 0.5	—
<b>AC/RF Isolation</b> (dB)	52-1002	-65	—
<b>RFI Isolation</b> (dB)	5-1002	-120	—
<b>Group Delay</b> (ns/3.58 MHz)	Ch. 2	16.0	—
	Ch. 3	8.0	—
	Ch. 4	5.0	—
	Ch. 5 & up	3.0	—
<b>Distortions<sup>1</sup></b>			
Composite Triple Beat		—	75
Composite Second Order		—	62
Cross Modulation		—	75
Hum Modulation		—	80
<b>Return Specifications</b>			
<b>Insertion Loss</b> (dB)	5-42	1.5	—
<b>Flatness</b> (dB)	5-42	± 0.5	—
<b>Return Loss</b> (dB)	5-42	—	20
<b>Group Delay</b> (ns/1.5 MHz)	5.0-6.5	20.0	—
	6.5-8.0	15.0	—
	8.0-34	5.0	—
	34-42	20.0	—

1. +10 dBmV flat input, 79 analog channels from 55 MHz to 550 MHz. Digital channels from 550 MHz to 750 MHz at 6 dB below the analog channels.

## Specifications ARA1-15EQ/AC

General	
Amplifier Type	Gallium Arsenide Technology
Nominal Impedance	75 Ω
F-connector Type	ANSI/SCTE 01 (Formerly SCTE IPS-SP-400) Compliant Sealed Brass CamPort®
Surge withstand	6 kV Combo Wave (IEEE C62.41-1991 Cat. B3) on all RF ports 6 kV Ring Wave (IEEE C62.41-1991 Cat. A3) on all ports and Power Adaptor
Power Adaptor	12 VDC/200 mA Output, UL Listed, PTC Short-Circuit Protected, Self-resetting
Dimensions, Weight	4.9" x 4.0" x 1.0", 1.0 lb
Environmental	
Pressure Seal	15 psi
Operating Temperature	-40 °C to +60 °C
Corrosion Resistance	Meets ANSI/SCTE Specification
Warranty	5 Years

## Ordering Guide

<b>ARA1-15EQ/AC</b>	1 Output, 120 VAC/60 Hz, 7 dB EO Amplifier
<b>ARPI-2000</b>	Power Inserter for Remote Powering
<b>AARAC-12N</b>	AC Power Adaptor, 120 VAC/60 Hz Input, 12 VDC Output

